

ENVIRONMENTAL
CONTROL

Gewa Andromeda

latest generation remote control receiver



*Well-known for long range
and
high reliability*



GEWA ANDROMEDA

is a further development of the familiar Gewalink system, well-known for long range and high reliability.

Gewa Andromeda is unique in combining infrared (IR) and radio (Gewa Radio) in the same receiver.

Gewa Andromeda has been designed to be easy to program, but it also has a number of advanced functions such as a mono/bistable function, switch-on display, and max/min response time.

It is possible to connect up to 5 separate IR detectors. It is also possible to connect external control switches for activating the relays.

GEWA ANDROMEDA IS AVAILABLE IN THE FOLLOWING MODELS

RECEIVER

Art.nr 419830 Andromeda IRZ-REC 4
IR and radio receiver for indoor installation.
4 relay outputs.

Art.nr 419835 Andromeda IRZ-REC 4 OUT
IR and radio receiver for outdoor installation.
4 relay outputs.

Art.nr 419850 Andromeda IRZ-REC 4 WM
IR and Radio receiver for indoor installation.
4 relay outputs. Specially adapted for window openers.

Art.nr. 419812 IR-REC 2
IR receiver for indoor installation.
2 relay output. Without Radio.

Art.nr 419860 Andromeda IR-DET 3
IR detector for indoor and outdoor installation.
3 meter cable.

Art.nr 419865 Andromeda IR-DET 15
IR detector for indoor and outdoor installation.
15 meter cable.

Art.nr 419872 Andromeda IR-DET
IR detector for indoor installation.
Without cable.

TECHNICAL DATA

Operating voltage:	12-24 V AC/DC (- 10% - +20%)
Max power consumption at rest:	60mA (2 detectors, inactive relays, active radio)
Max power consumption:	120mA (2 detectors, 4 active relays, active radio)
Max relay load:	3A, 24V AC/DC resistive load
Max detectors:	6 including built-in detector
Programming channels:	GewaLink channels 0-127, 4096 code and Gewa Radio
Ambient temperature:	-20°C - +35°C

> **MORE INFORMATION:** visit our homepage